



## Connection Policy – Connection Charges

July 2017



### SCOPE

This publication sets out the connection charges payable by customers for connecting their premises to Ausgrid's distribution network.

### WARNING

It is the responsibility of the user of this document to ensure that only the current version is being used.

### DOCUMENT AND AMENDMENT HISTORY

Issue No.	Date	Approved by	Summary of Changes
1	26 June 2015	Chief Engineer	Initial Issue
2	02 July 2015	Chief Engineer	Numbering of main headings adjusted and missing item B13 added to Table 2
3	30 July 2015	Chief Engineer	Appendix F added, formatting changes, cross-referencing updated
4	22 Sept 2015	Chief Engineer	Reference to the definition of "contestable" updated (P13); Appendix E referencing updated.
5	01 June 2016	Acting Chief Engineer	Charges updated as per Ausgrid's Undertaking to the AER. Approved by the AER 16 May 2016.
6	01 July 2017	GM/ Asset Management & Operations	ANS charges updated as per AER approval and 2015-2019 Determination requirements.

ISSN 1032-7215

Published and printed by Ausgrid.

Copyright ©, Ausgrid.

This document can be freely downloaded from [www.ausgrid.com.au](http://www.ausgrid.com.au)

All correspondence should be directed to:

General Manager/ Asset Management and Operations

Ausgrid

GPO Box 4009

SYDNEY NSW 2001

## CONTENTS

1	INTRODUCTION .....	4
	1.1 General approach to funding connections .....	4
	1.2 Connection Charges .....	5
2	FUNDING OF CONNECTION WORKS & NETWORK AUGMENTATIONS .....	6
	2.1 Basic Connection Offers .....	6
	2.2 Standard Connection Offers .....	6
	2.3 Negotiated Connection Offers .....	7
	2.4 Contestability of Connection Works .....	7
	2.5 Connection Works Funded by Ausgrid .....	7
	2.6 Customer Requested Alternative or Additional Connection Works .....	7
3	CAPITAL CONTRIBUTION THRESHOLDS .....	8
	3.1 Capital Contribution Thresholds .....	8
	3.1.1 Real Estate Developments and Embedded Generators .....	8
	3.1.2 <i>Retail Customer</i> Network Thresholds for Urban Areas .....	8
	3.1.3 Threshold for Rural Customers .....	9
	3.1.4 When Ausgrid Will Fund Connection Costs .....	9
	3.2 Calculation of Capital Contributions .....	9
	3.3 Calculation of Connection Applicants Maximum Demand .....	10
4	ANCILLARY SERVICES AND FEES .....	10
5	METERING SERVICES .....	10
6	OTHER FEES .....	11
7	PIONEER SCHEMES .....	11
8	FINANCIAL GUARANTEES (SECURITY FEES) .....	11
9	PREPAYMENTS .....	12
10	DISPUTE RESOLUTION .....	12
	DICTIONARY .....	13
	APPENDIX A: SUMMARY OF AUSGRID'S CONNECTION OFFERS AND THEIR ASSOCIATED CONNECTION CHARGES .....	15
	APPENDIX B: CONNECTION RELATED ANCILLARY SERVICES .....	16
	APPENDIX C: METERING SERVICES AND METERING RELATED ANCILLARY SERVICES .....	27
	APPENDIX D: MISCELLANEOUS ANCILLARY SERVICES .....	30
	APPENDIX E: PIONEER SCHEMES .....	36
	APPENDIX F: NEGOTIATED CONNECTION OFFER HOURLY RATES .....	40

# 1 Introduction

This document is Ausgrid's Connection Policy.

This connection policy sets out the circumstances in which Ausgrid requires a retail customer or real estate developer to pay the cost of connecting their premises or development to the Ausgrid network. The costs are also known as connection charges for the provision of connection services under chapter 5A of the National Electricity Rules (*NER*).

A connection charge can be a fee payable to Ausgrid for a service, such as an inspection or it could be a financial guarantee where Ausgrid has carried out an *augmentation* to its network.

This policy has been prepared to be consistent with the following regulatory instruments, which regulate the fees and charges that Ausgrid can require a customer to pay:

- The connection charge principles set out in Part E-Connection charges, of chapter 5A of the *NER*,
- Part DA-Connection policies, of chapter 6 of the *NER*,
- The Australian Energy Regulator's (*AER's*) Connection charge guidelines for electricity retail customers, under chapter 5A of the *NER*, and
- The *AER's* determination for the 2015-19 regulatory control period in relation to the fees that Ausgrid can charge for Ancillary Services and Metering Services.

## 1.1 General approach to funding connections

The fees and charges payable by a customer in order to connect to Ausgrid's network fall into two categories:

1. Third party fees and charges that relate to the services provided by Accredited Service Providers (*ASP*) and other third parties in relation to the provision and installation of network infrastructure; and
2. Ausgrid's fees and charges for connection services provided by Ausgrid.

A brief description of these fees and charges is set out below.

### Third party fees and charges

The third party fees and charges are not payable to Ausgrid and, therefore, are not connection charges. They have been included in the connection policy to assist the customer to understand the scope of charges the customer may incur in establishing a connection to Ausgrid's network.

#### *Contestable services provided by Accredited Service Providers*

As a general rule, the services required to establish a customer's connection to Ausgrid's network are undertaken by Accredited Service Providers (*ASP*) and are known as *contestable* services. This means customers must fund the costs of *connection works* (i.e. make capital contributions), which include the following costs associated with establishing a new or altered connection of their installation or development to Ausgrid's network:

- The costs of providing and installing the necessary *premises connection assets* at the customer's connection point or point of supply and also within the customer's electrical installation, and
- The costs of providing and installing a dedicated extension from the connection point up to a defined point of connection on Ausgrid's existing network known as the *linkage point*.

The capital contributions payable by the customer for these *contestable* services are not specified in this Policy and are payable directly to the *ASP*.

### Network Augmentations

Generally Ausgrid carries out and funds augmentation to the shared network. This is work on the shared assets beyond the *linkage point*. Connection applicants will be required to fund augmentation in the following circumstances:

- All real estate developers must fund augmentation work.
- Non registered embedded generators must fund augmentation work.
- Retail customers: If the capacity applied for by the connection applicant exceeds the thresholds set by Ausgrid in Section 3 of this policy, they will be required to make a capital contribution towards the cost of the augmentation of Ausgrid's shared network.

In all cases:

- The capital contribution will be limited to the augmentation required to enable the connection to be made.
- The augmentation work is *contestable* and undertaken by an *ASP* so the capital contribution is payable to the *ASP*, not to Ausgrid.

#### *Other third party fees and charges*

In addition to ASP charges, the customer may also incur property tenure costs that relate to the granting and registration of leases and easements and associated plans over Ausgrid infrastructure that is located on the customer's premises. These costs are also not payable to Ausgrid but directly to the relevant third party.

#### **Ausgrid's fees and charges**

##### *Ancillary service fees*

Ancillary services are services that are non-routine connection services provided to a customer on an "as needs" basis. These services can only be undertaken by Ausgrid. All customers will be required to pay the fees for *ancillary services* associated with their connection. These fees relate to the services that Ausgrid provides during the design and construction (on a *contestable* basis) of premises connection assets, *extensions* and *augmentation* by ASPs. An example would be inspection of assets built by a Level 1 ASP. These services and fees are explained in detail in section 4.

##### *Metering service fees*

Other than metering related Ancillary Services, the only relevant metering services provided by Ausgrid in relation to connection services is the provision of the meter. The customer must fund the cost of the meter that is approved by the AER. See section 5 for further details.

##### *Other fees*

In some circumstances customers may be required to pay a fixed site inspection fee if a site inspection is required. Customers who receive a negotiated connection offer can be required to pay Ausgrid's reasonable expenses in assessing the customer's connection application and preparing the offer. Ausgrid's approach to determining its reasonable expenses is set out in section 6.

##### *Pioneer scheme payments*

*Retail customers* or *real estate developers* who propose to connect to a part of the network funded by another customer in the previous 7 years (a pioneer scheme) may be required to make a payment to connect to the pioneer scheme. See section 7.

##### *Financial guarantees*

In some circumstances, Ausgrid may require a customer to provide Ausgrid with a financial guarantee known as a Guarantee of Revenue (GoR) which guarantees Ausgrid a certain level of revenue in relation to a substantial *augmentation* that Ausgrid has funded in order for the customer to connect. See section 8.

#### **Charges for Ongoing Supply Services**

For information purposes only, this Policy also sets out miscellaneous fees that Ausgrid may charge once a new or altered connection has been energised. These fees are explained in section 4 and Appendix B.

#### **Note:**

This Policy does not apply to connections to Ausgrid's network by registered participants or intending registered participants in the wholesale market. These connections are covered by the provisions of chapter 5 Network Connection, of the *NER*.

## **1.2 Connection Charges**

The connection charges that customers seeking a new or altered connection of their premises to Ausgrid's distribution system are required to pay to Ausgrid are:

1. Ancillary service fees for all ancillary services provided by Ausgrid in order for the customer to connect – see section 4;
2. Metering service fees for the provision of the meter required for the connection – see section 5;
2. Other fees if a site inspection is required and/or negotiation fee for a negotiated connection offer – see section 6;
3. Pioneer scheme payment if a pioneer scheme exists for the assets to which the customer connects – see section 7;
4. In addition the customer may also be required to provide Ausgrid with a financial guarantee in certain circumstances where Ausgrid funds a network augmentation – see section 8.

## 2 Funding of Connection Works & Network Augmentations

For ease of reference Ausgrid has described the types of connection works and services that customers must fund by reference to whether the costs are incurred in relation to a basic connection services or standard connection services.

The charges for basic connection services are generally uniform and confined to funding premises connection assets and paying ancillary service fees and metering service fees as the connections to which they relate do not require any network *augmentation* other than *extensions* for premises connection assets.

The charges for standard connection offers also include the *extension* and *augmentation* costs as well as funding premises connection assets and ancillary service fees and metering service fees. The *augmentation* costs are determined by reference to a capital contribution threshold set by Ausgrid.

Appendix A provides a summary of the fees and charges payable in relation to each connection offer.

### 2.1 Basic Connection Offers

These offers are typically applicable to single residential premises, small commercial premises and small multi-occupant developments. They are also applicable to customers who install a micro embedded generator within their installation.

Customers who receive one of Ausgrid's basic connection offers will be required to fund the *contestable* works (i.e. make a capital contribution) associated with:

- their *premises connection assets*, and
- any dedicated network *extension*.

These customers will not be required to fund any *augmentation* of Ausgrid's shared network beyond the linkage point. The capital contributions made by the customer are payable directly as charges to the *ASP* and are not set out in this Policy.

The customer must also pay any ancillary service fees and metering service fees associated with their connection. These are explained in detail in section 4 and Appendix B.

In some circumstances a site inspection fee or pioneer scheme payment may also be required.

The *contestable* work required to install or alter the customer's premises connection assets and any dedicated network *extension* will be carried out by the customer's *ASP*. This includes the provision of the service line and installation of the meter by the customer's Level 2 *ASP*, refer to Appendix A.

### 2.2 Standard Connection Offers

These offers are typically applicable to large multi-occupant developments, and large commercial and industrial developments as well as rural customers who require augmentation work.

Ausgrid's standard connection offers apply to connections where an *augmentation* of Ausgrid's shared network may be required to enable the customer's connection to occur.

In addition, if a low voltage network extension is required that involves design by a Level 3 *ASP* and/or construction by a Level 1 *ASP* then a standard connection offer will be made.

Customers who receive standard connection offers will be required to fund the *contestable* works (i.e. make a capital contribution) associated with:

- their *premises connection assets*,
- any dedicated network *extension*, and
- in relation to *real estate developers* and non-registered embedded generators, any *augmentation*;
- in relation to *retail customers*, any *augmentation* of the shared network, if the capacity applied for exceeds the thresholds set out in section 3.

Different thresholds apply to *retail customers* depending on whether the connection is in an urban or rural area.

Ausgrid will fund the shared *augmentation* works if a customer applies for a capacity below the threshold set out in section 3. This threshold has been established by Ausgrid to meet the requirements of clause 5A.E.1(b)(2) of the *NER* to indicate the threshold below which a *retail customer* will not be required to make a capital contribution towards the cost of the shared network *augmentation*.

The customer must also pay for ancillary service fees and metering service fees associated with their connection. These are explained in detail in section 4 and Appendix B.

In some circumstances a site inspection fee (see section 6) or pioneer scheme payment may also be required as explained in section 7 and Appendix E respectively.

Some customers may also be required to provide a financial guarantee or Guarantee of Revenue (GoR), where their connection requires substantial Ausgrid funded *augmentation* works. The circumstances in which a GoR may be required are set out in more detail in section 8.

The *contestable* work required to design and construct customer funded augmentation works will be carried out by the customer's Level 3 and Level 1 *ASPs* respectively. The capital contributions associated with the contestable works are payable as charges directly to the relevant *ASP* and are not set out in this Policy.

Ausgrid will require reasonable prepayment of ancillary service fees associated with standard connection offers – see section 9. Ancillary service fees are listed in the tables at the end of this connection policy.

### 2.3 Negotiated Connection Offers

Customers who receive a negotiated connection offer from Ausgrid will be required to pay connection charges to Ausgrid and/or make capital contributions to the *ASP* for the *connection works* on the same basis as for customers who receive basic or standard connection offers.

In addition, these customers may also be required to pay a negotiation fee to cover the expenses reasonably incurred by Ausgrid in assessing the customer's application and preparing a negotiated connection offer. The fee is quoted on the basis of an hourly rate and is listed in Table 8.

Customers who receive a negotiated connection offer may be required to provide a financial guarantee or GoR, where their connection requires substantial Ausgrid funded *network augmentation* works. The circumstances in which a GoR may be required are set out in more detail in section 8.

Ausgrid will require reasonable prepayment of ancillary service fees associated with a negotiated connection offer – see section 9. Ancillary service fees are listed in the tables at the end of this connection policy.

### 2.4 Contestability of Connection Works

Under section 31 of the Electricity Supply Act 1995, where a customer is required to procure and fund *connection works* or *network augmentations*, the customer may do this by engaging an *ASP* to design and/or construct those works as *contestable* works. The *ASP* must be suitably accredited under the NSW Accreditation Scheme administered by the NSW Department of Industry, Skills and Regional Development (NSW Department of Industry).

The customer pays the *ASP* directly for these services including for any assets installed (i.e. a capital contribution).

### 2.5 Connection Works Funded by Ausgrid

Ausgrid may determine that certain *connection works* or portions thereof that are *augmentation* that would normally be funded by customers and provided on a *contestable* basis will be carried out and funded by Ausgrid. Ausgrid will make this determination based on risk management principles related to certain criteria such as safety, network security and reliability of supply to customers.

Based on a risk assessment by Ausgrid, the following categories of connection works may be carried out and funded by Ausgrid:

- Design and construction of underground gas and oil sub transmission cables
- Design and construction of overhead steel lattice tower sub transmission lines
- All High Voltage (HV) cable identification, stabbing and phasing
- HV testing of installed 11kV underground polymeric cables prior to commissioning, where the cables are to be locally energised at existing Ausgrid substations
- All work within existing substations including pole transformer substations that are connected to the network and are energised
- Induced HV tests on new transformers supplied and funded by Ausgrid and delivered to site by the manufacturer
- Minor capital street lighting projects
- Based on an individual risk assessment carried out by Ausgrid, certain major projects such as transmission, sub-transmission, zone substation, and Sydney CBD projects.
- Optical fibre termination.

### 2.6 Customer Requested Alternative or Additional Connection Works

Ausgrid specifies the economic optimum size *connection works* in accordance with its network standards, to adequately supply the assessed electrical load requirements of customers. However, if a customer requests any alternative or additional *connection works* to the standard Ausgrid construction, and Ausgrid agrees with the request, the customer will be required to fund any additional costs thereby incurred by Ausgrid. This includes the

additional cost of any alternative or additional HV equipment that would otherwise be funded by Ausgrid in accordance with clause 2.5.

### 3 Capital Contribution Thresholds

A capital contribution is a payment made by a customer towards the cost of a connection to Ausgrid's network. In NSW, where a customer is required to fund connection works, the customer can engage an *ASP* to undertake the works (known as *contestable* services). This means the capital contribution is payable to the *ASP*, not Ausgrid. This Policy sets out the circumstances when a capital contribution is payable. The amount of the capital contribution is separately determined between the customer and the *ASP* and is outside the scope of this Policy.

A *retail customer* (other than a *real estate developer* or a non-registered embedded generator) will not be required to make a capital contribution towards the cost of *augmentation* (to the extent it involves more than an extension) if:

- the connection services being sought by the connection applicant are basic connection services; or
- the capital contribution thresholds set by Ausgrid are not exceeded.

#### 3.1 Capital Contribution Thresholds

Ausgrid has established two thresholds below which *retail customers* will not be required to make a capital contribution towards the cost of network augmentations:

1. A customer substation threshold for urban areas; and
2. A rural threshold for customers in rural areas.

The Capital Contribution Thresholds will apply for the 2015-19 regulatory control period.

##### 3.1.1 Real Estate Developments and Embedded Generators

Real estate developments and embedded generators that cannot be supplied by the adjacent Ausgrid network will be required to fund a substation on the development or additional capacity in the vicinity of the development or embedded generator.

In this case Ausgrid will require the connection applicant to fund as *contestable* works:

- For onsite substations: The design and construction by an *ASP* of the substation and a network extension consisting of the dedicated HV mains to the substation;
 

Note: The standard reticulation is a loop-in arrangement, i.e. 2 cables, or if an alternative arrangement consisting of a single (radial) HV cable connection and a Low Voltage (LV) interconnector is agreed to by Ausgrid, this LV interconnector will also be funded by the customer.
- For other network augmentations in the vicinity of the premises: The design and construction of any network augmentations that are required to make the required capacity available at the premises of the connection applicant;
- The substation building construction for chamber substations; and any site preparation works, including special foundations, footings, piers, retaining walls and railings for kiosk substations.

The connection applicant must provide a suitable substation site on their premises as close as possible to the street frontage where requested by Ausgrid.

##### 3.1.2 Retail Customer Network Thresholds for Urban Areas

Ausgrid has adopted the following threshold to determine when a *retail customer* must contribute to the cost of expanding the capacity of the Ausgrid network (i.e. make a capital contribution):

###### **Retail Customer > 100 Amps**

Where a *retail customer* in an urban network requires 100 Amps or more (per phase over 3 phases) and the adjacent Ausgrid network cannot supply the required load, the customer will be required to fund either:

- One or more new substations on or in the vicinity of the premises of the development;
- Additional network capacity in the vicinity of the premises of the development.

This will require the customer to fund as *contestable* works:

- For onsite substations: The design and construction by an *ASP* of the substation and a network extension consisting of the dedicated High Voltage (HV) mains to the substation;
 

Note: The standard reticulation is a loop-in arrangement, i.e. 2 cables, or if an alternative arrangement consisting of a single (radial) HV cable connection and an LV interconnector is agreed to by Ausgrid, this LV interconnector will also be funded by the customer.



- For other network augmentations in the vicinity of the development: The design and construction of network augmentations that are required to make the required capacity available at the premises of the development
- The substation building construction for chamber substations and any site preparation works, including special foundations, footings, piers, retaining walls and railings for kiosk substations.

The nature and scope of the additional capacity will be determined by Ausgrid to meet the proposed customer load and Ausgrid network requirements.

The new substations or additional network capacity will be designed to be the minimum economic size or accommodate the minimum number of transformers necessary to supply the ultimate forecast load requirements of the proposed development.

### 3.1.3 Threshold for Rural Customers

*Rural customers* are required to fund any shared *network augmentation* that is required for their connection where the customer's new load is greater than 25 kVA single phase.

*Rural customers* must also fund any *augmentation* by way of any required dedicated customer substation equipment. If this substation is likely to supply the surrounding network in the next 7 years Ausgrid will contribute to its cost on a pro rata basis. A pioneer scheme will be implemented with respect to either *connection works* or shared *network augmentation* works funded by *rural customers*, as outlined in Appendix E.

Ausgrid's Model Standing Offer: *Standard Connection Services for Contestable ASP/1 Premises Connections no greater than 11 kV* has been prepared to apply to this type of connection.

### 3.1.4 When Ausgrid Will Fund Connection Costs

However, Ausgrid will refund the connection applicant a proportion of the customer's costs (outlined above), corresponding to the spare or unused capacity of the substation or other augmentation, which is available and likely to supply general network load external to the development within the next 7 years, once the ultimate forecast load of the customer has been supplied. This refund will exclude the cost of any ancillary service fees and the value of the land/space made available for the substation. This amount will be determined upfront by Ausgrid using standard rates and consistent with its 2015-19 regulatory determination that regulates revenues for standard control services and will be included in the relevant connection offer. In these circumstances where Ausgrid provides a refund for connection applicant funded works, the substation will not be eligible for a pioneer scheme (see section 7) and the customer will not be entitled to a pioneer scheme payment if subsequent customers connect to the relevant connection assets.

Ausgrid's Model Standing Offer: *Standard Connection Services for Contestable ASP/1 Premises Connections no greater than 11 kV* has been prepared to apply to this type of connection. There is no basic or standard model standing offer for connections greater than 11 kV, these will require a negotiated connection offer.

The connection applicant must provide a suitable substation site on their premises as close as possible to the street frontage where requested by Ausgrid.

Should the premises providing the substation accommodation, require increased load in the future, the connection applicant may be required to contribute to the direct costs of reconnecting some or all of the load external to the premises, in order to supply the customer's load.

Connection applications from *retail customers* in an urban network for up to and including 100A will not be required to contribute to the cost of a new substation. An example would be a single dwelling requiring less than 100A.

## 3.2 Calculation of Capital Contributions

This Policy sets out the circumstances when a capital contribution will be payable by a customer. It does not set out how the amount of any capital contribution is calculated because the customer does not pay Ausgrid a capital contribution. When a customer is required to make a capital contribution, the connection work related to the contribution is a *contestable* service in NSW and the customer engages an *ASP* to undertake the work. The customer pays the capital contribution to the *ASP* and the cost is determined on a competitive basis.

Capital contributions arise in the following circumstances:

- by real estate developers and non-registered embedded generators for all connection works including extensions and augmentations;
- by retail customers below the Capital Contribution Thresholds identified in section 3.1 (i.e. for premises connection assets and extensions);
- by retail customers above the Capital Contribution Thresholds identified in section 3.1.

In circumstances where Ausgrid funds an *augmentation*, the service provided is classified by the *AER* as a *standard control service*. The *AER* Connection Charge Guidelines allow Ausgrid to seek a capital contribution from a customer if the incremental cost of the service provided exceeds the estimated incremental revenue

expected to be derived from the service. Ausgrid does not seek a capital contribution from customers in these circumstances as the incremental cost does not exceed the incremental revenue.

The capital contributions made by customers by way of charges to the *ASP* are set on a competitive basis. If Ausgrid agrees to refund the customer for capital contributions made by customer (e.g. Ausgrid uses the spare capacity), the refund is not a capital contribution and is determined by Ausgrid in accordance with its 2014-15 transitional regulatory determination that regulates the recovery of revenue for standard control services (which is the service provided by the network augmentation).

If a pioneer scheme relates to the assets for which the customer has made a capital contribution, the customer may be entitled to a pioneer scheme refund. See section 7.

### 3.3 Calculation of Connection Applicants Maximum Demand

When a connection applicant submits a connection application to Ausgrid they are required to also submit maximum demand calculations in accordance with AS/NZS3000. For larger developments the maximum demand worksheet must be included with the connection application. Ausgrid will use the maximum demand calculations provided by the applicant to determine the appropriate connection offer that will be made and the capital contribution threshold that will apply. Ausgrid does not use consumption calculations to determine the appropriate threshold that will apply.

## 4 Ancillary Services and Fees

Ancillary Services provided by Ausgrid fall into 3 categories:

1. Ancillary Services that are required in order for a customer to connect to Ausgrid's network (Connection related Ancillary Services);
2. Ancillary Services that are provided to customers as part of their ongoing supply service provided by Ausgrid under a different contract (Miscellaneous Ancillary Services); and
3. Metering related Ancillary Services that are ancillary services relating to the provision, installation and maintenance of metering installations.

### Connection related Ancillary Services

These are customer specific connection services that only Ausgrid can perform, which facilitate *contestable connection works* carried out by *ASPs* and which are required for Ausgrid to connect. These services are necessary to ensure that an appropriate level of reliability, quality of supply and safety is maintained in the operation of Ausgrid's *network*. The *AER* reviews and approves these services and sets their rates and conditions. These services were previously known as Monopoly Services but since 1 July 2014 are known as Ancillary Services.

The charges for ancillary services are approved by the *AER* for each financial year and are included in Appendix B.

### Miscellaneous Ancillary Services

These Ancillary Services are provided by Ausgrid on "as needed" basis to the customer after the connection has been established. These ancillary services are not part of the connection service provided under Chapter 5A of the *NER* and are not connection charges under Chapter 5A.

These services are included in this Policy for information and are payable by the customer under its ongoing supply contract with Ausgrid. A full list of these services is contained in Appendix D.

### Ancillary Services related to Metering

Ausgrid also provides Ancillary Services that specifically relate to metering, such as carrying out special meter readings and meter testing. It also provides and installs current transformer (CT) metering. The charges for these services are set out in Appendix C.

## 5 Metering Services

Other than the metering related Ancillary Services, the only other relevant metering service provided by Ausgrid in relation to connection services is the provision of the meter required for the connection. The customer is required to fund the cost of the provision of a meter, if supplied by Ausgrid. The charge payable by the customer is called a new or upgraded metering charge. It is approved by the *AER* for each financial year and is in Appendix C.

The service relating to the installation of the meter is provided by an *ASP* and the cost of the service is payable to the *ASP*. Other metering services provided by Ausgrid are payable by the customer as part of the customer's ongoing supply network charges and are not subject to this connection policy.

## 6 Other fees

Chapter 5A of the National Electricity Rules allows Ausgrid to charge certain fees to recover its costs from connection services relating to processing the connection application.

### Site inspection fee

Where Ausgrid reasonably needs to make a site inspection in order to determine the nature of the connection service sought by the connection applicant, Ausgrid may charge its reasonable expenses to the connection applicant and recover those expenses as a debt.

Ausgrid charges a fixed fee for site inspection fees which is based on its costs to attend and assess the proposed connection site. This fee is \$370 for urban areas and \$650 for rural areas.

### Negotiation fee

Where a connection applicant has elected to enter into a negotiated connection contract under Chapter 5A, Ausgrid may charge the applicant a reasonable fee to cover expenses directly and reasonably incurred by Ausgrid in assessing the applicant's application and making a connection offer.

Ausgrid has established an hourly rate that reflects the various input costs involved in processing a negotiated connection application and offer. Ausgrid then multiplies this rate by the number of hours spent by the various Ausgrid staff in assessing the negotiated connection application and preparing the negotiated connection offer. The hourly rates are in Table 8.

## 7 Pioneer schemes

Under Chapter 5A, Ausgrid is required to operate a pioneer scheme that requires Ausgrid to make refunds to retail customers who funded connection assets within 7 years that are no longer being dedicated to the exclusive use of that customer. The refund is made by way of a connection charge (known in this Policy as a pioneer scheme payment) payable by the new users of the assets.

Appendix E sets out how Ausgrid calculates the pioneer scheme payments and refunds in respect of assets that are subject to a pioneer scheme.

## 8 Financial Guarantees (Security Fees)

In accordance with chapters 5A and 6 of the *NER* Ausgrid will require a customer to provide a financial guarantee (also known as security fee) or GoR, where their connection requires substantial Ausgrid funded *network augmentation* works (nominally \$1M or more) that is initially only for the customer's benefit. In these circumstances Ausgrid considers there is a high risk that Ausgrid may not earn the estimated incremental revenue from the construction of the *network augmentation* works.

Generally a GoR will only be required in relation to connections that are the subject of a negotiated connection offer.

A GoR is a binding legal agreement between Ausgrid and the connection applicant where the connection applicant guarantees to pay Ausgrid a minimum level of network revenue each year for the duration of the GoR agreement, to make up any shortfall in their actual Network Use of System (NUoS) charges over the period, which is nominally 5 years, although this can be varied between 5 and 10 years on a case by case basis. The security amount will not be greater than the present value of the incremental costs that Ausgrid incurred by Ausgrid in undertaking network augmentation. The security amount under the GoR is calculated by reference to the incremental revenue Ausgrid expects to receive from the network augmentation. The security amount will not be greater than the amount of the estimated incremental revenue that Ausgrid assesses as having a high risk of not being recovered.

The GoR will be established at the same time as the design information package is issued and prior to the *network augmentation* works being initiated. This will allow the *network augmentation* works to proceed in parallel with the associated *contestable* works.

The GoR is secured by a bank guarantee provided by the customer, or other suitable financial instrument as agreed by Ausgrid. Ausgrid is entitled to withdraw from the bank guarantee any shortfall in actual NUoS payments, in accordance with the terms stated in the deed and the bank guarantee.

## 9 Prepayments

Ausgrid will only seek prepayments in circumstances that are permitted by the regulatory environment and in particular Chapter 5A and the *AER* Connection Charge Guidelines.

Ausgrid will seek upfront payment of a customer's ancillary service fees for design work when the design contract is accepted by the connection applicant.

Ausgrid will seek reasonable upfront payment of ancillary service fees when a connection offer is made or before construction starts.

If the *connection works* can be logically segmented into distinct stages of construction then a payment schedule that aligns with the construction stages will be negotiated.

## 10 Dispute Resolution

A dispute between a retail customer or a real estate developer and Ausgrid about connection charges is an access dispute for the purposes of section 2A of the National Electricity Law, which may be referred to the *AER* for resolution in accordance with part G of chapter 5A of the *NER*.

Prior to referring the matter to the *AER*, Ausgrid encourages customers to first attempt to resolve the dispute directly with Ausgrid, in accordance with the internal dispute resolution policy we have adopted for reviewing any decision Ausgrid makes that may affect customers. Details of how to apply for review of a decision by Ausgrid and how Ausgrid will conduct the review are available on Ausgrid's website <http://www.ausgrid.com.au/connectingtothenetwork> and click on the link "Lodging a complaint".

If you are a small customer you may also refer your dispute to the Energy and Water Ombudsmen NSW (EWON) to resolve the matter.

## Dictionary

### A note on terms and definitions

As far as possible, Ausgrid has used terms and definitions that are consistent with chapter 5A of the *NER*. So for instance we use the term “*premises connection assets*” to refer to the works required to extend Ausgrid’s network to enable a connection to occur that are substantially located on a customer’s premises and generally dedicated to connecting that customer. However, in some instances we also use other terms, such as “*linkage point*” as these terms are necessary to explain the extent to which a customer funds *premises connection assets*, *extensions* and *augmentations*.

The terms shown in *italics* throughout this document have the following meanings:

<b><i>ancillary services</i></b>	As per <i>NER</i> Chapter 10 definition
<b><i>augmentation</i></b>	Work to enlarge a distribution or transmission system or to increase its capacity to transmit or distribute electricity
<b><i>AER</i></b>	The Australian Energy Regulator
<b><i>ASP</i></b>	An Accredited Service Provider, being a person accredited under Part 10 of the Electricity Supply (General) Regulation 2001 (NSW)
<b><i>connection works</i></b>	In relation to a new customer, are those works yet to be constructed that will, upon construction: <ul style="list-style-type: none"> <li>(a) enable Ausgrid to provide customer connection services requested by that new customer; and</li> <li>(b) form part of the network on the side of the <i>linkage point</i> where all the network assets on that side are dedicated to one or more customers.</li> </ul> <p>These include (without limitation):</p> <ul style="list-style-type: none"> <li>(c) in the case of services to new connection points (as defined in the National Electricity Rules) requested by a new customer, works to connect the customer’s premises at that connection point to the existing network; and</li> <li>(d) in the case of services to existing connection points:             <ul style="list-style-type: none"> <li>replacements of existing assets servicing that connection point, where those existing assets, at the time of their replacement, satisfy (a) and (b) above; or</li> <li>additional new works that satisfy (a) and (b) above in relation to that connection point,</li> </ul> <p>in order to provide additional service at that connection point requested by the new customer.</p> </li> </ul>
<b><i>contestable</i></b>	As per <i>NER</i> Chapter 5A definition
<b><i>extension</i></b>	New network infrastructure outside the present boundaries of Ausgrid’s network to a customer’s premises.
<b><i>linkage point</i></b>	The point on the network where the use of assets changes from being dedicated to one or more customers (where all the network assets on that side of the point are dedicated), to being shared with customers generally. For this purpose, assets are considered to be dedicated to one or more customers only if they are: <ul style="list-style-type: none"> <li>(a) used by one customer exclusively; or</li> <li>(b) shared by more than one customer in circumstances where Ausgrid has required that those customers together procure and fund the same connections works</li> </ul>
<b><i>NER</i></b>	The National Electricity Rules
<b><i>network</i></b>	Ausgrid’s electricity distribution system
<b><i>premises connection assets</i></b>	As per <i>NER</i> Chapter 10 definition
<b><i>real estate developers</i></b>	As per <i>NER</i> Chapter 10 definition

<b>retail customers</b>	As per <i>NER</i> Chapter 10 definition
<b>rural customer</b>	A new customer whose premises, the subject of its application for customer connection services, are connected or will be connected (once any relevant connection works are constructed) to the network at a point at which the network is a <i>rural network</i> .
<b>rural network</b>	That part of the network: <ul style="list-style-type: none"><li>(a) that is in an area zoned as rural under a local environment plan (made under the Environmental Planning and Assessment Act 1979 (NSW)); or</li><li>(b) that is in an area predominantly used for agricultural purposes</li></ul>
<b>urban network</b>	That part of the network that is not a <i>rural network</i> .

## Appendix A: Summary of Ausgrid’s connection offers and their associated connection charges

Table 1: Summary of Ausgrid’s connection offers and their associated connection charges

Connection Offer	Typical example or application	Fees and charges involved in establishing connection	Contestable work carried out by:
<b>Basic:</b>			
1. Model Standing Offer Basic Connection Services – 100 Amps Connections	<ul style="list-style-type: none"> <li>single home</li> <li>small shop</li> </ul>	<ul style="list-style-type: none"> <li>Installation of dedicated premises connection assets, payable to the customer’s Level 2 ASP</li> <li>Ancillary service fees associated with the <i>contestable</i> work, payable to Ausgrid</li> <li>Fee for new or upgraded meter</li> <li>Site inspection fee payable to Ausgrid, if a site inspection is performed</li> <li>Pioneer scheme costs as applicable</li> </ul>	Level 2 ASP, for the installation of the dedicated premises connection assets i.e. the service line and the Type 5 whole current metering, and energising the connection <b>NB.</b> <ul style="list-style-type: none"> <li>Ausgrid installs Type 5 current transformer metering at no charge to the customer<sup>1</sup></li> <li>The retailer arranges for the installation of Type 4 whole current or current transformer metering and charges the customer accordingly</li> </ul>
2. Model Standing Offer Basic Connection Services – Connections over 100 Amps	<ul style="list-style-type: none"> <li>small multi-occupant development</li> <li>medium commercial or industrial developments</li> <li>large multi-level premises load increase</li> </ul>		
3. Model Standing Offer Basic Connection Services – Micro EG Connections	<ul style="list-style-type: none"> <li>roof-top solar panel installation</li> </ul>		
<b>Standard:</b>			
1. Model Standing Offer Standard Connection Services for Contestable ASP/1 Premises Connections no greater than 11kV	<ul style="list-style-type: none"> <li>A customer connection involving <i>contestable</i> services.</li> </ul>	<ul style="list-style-type: none"> <li>Premises connection assets payable to ASP, refer to section 3 for customer substation thresholds,</li> <li>Network augmentation or <i>extension</i> payable by ASP, refer to section 3 for associated customer network thresholds, and</li> <li>Pioneer scheme costs as applicable Ancillary service fees associated with the <i>contestable</i> work, payable to Ausgrid</li> <li>Fee for new or upgraded meter</li> <li>Site inspection fee payable to Ausgrid, as applicable</li> <li>Property tenure costs payable to third parties</li> <li>A GoR may be required if the connection requires substantial Ausgrid funded <i>network augmentation</i> works, see section 8</li> </ul>	Level 3 and Level 1 ASP, for the design and construction of the premises connection assets, network <i>extension</i> and <i>network augmentation</i> assets, as applicable
2. Model Standing Offer Standard Connection Services – Ausgrid augmentation works including on-site substations	<ul style="list-style-type: none"> <li>A customer connection or alteration that requires an Ausgrid funded on site substation.</li> </ul>		
3. Model Standing Offer Standard Connection Services – Ausgrid augmentation (substation upgrade) works	<ul style="list-style-type: none"> <li>A customer connection alteration (load increase) where the customer has an onsite substation</li> </ul>		
4. Model Standing Offer Standard Connection Services – Ausgrid off-site augmentation works	<ul style="list-style-type: none"> <li>A new connection or connection alteration requiring Ausgrid funded augmentation works in the nearby network.</li> </ul>		
<b>Negotiated:</b>			
In accordance with Ausgrid’s Connection Negotiation Process, and the negotiation framework in chapter 5A of the <i>NER</i>	<ul style="list-style-type: none"> <li>Large commercial or industrial complex</li> </ul>	<ul style="list-style-type: none"> <li>As above for the standard offer, plus</li> <li>Negotiation expenses, payable to Ausgrid</li> <li>A GoR may be required if the connection requires substantial Ausgrid funded <i>network augmentation</i> works, see section 8</li> </ul>	As above for the standard offer

<sup>1</sup> Under review by the AER

## Appendix B: Connection Related Ancillary Services

Table 2: Charges for ancillary services associated with *contestable* connection and asset relocation works (prices include GST)

Clause	Ancillary service	Underground urban residential subdivision (vacant lots)	Rural overhead subdivisions and rural extensions	Underground commercial and industrial or rural subdivisions (vacant lots - no development)	Commercial and industrial developments	Asset relocation or street lighting
B1	Design Information	Underground urban residential subdivision (vacant lots) (per service)	Rural overhead subdivisions and rural extensions (Quoted - hourly rate)	Underground commercial and industrial or rural subdivisions (vacant lots - no development) (Quoted - hourly rate)	Commercial and industrial developments (Quoted - hourly rate)	Asset relocation or street lighting (Quoted - hourly rate)
		Up to 5 lots \$512.95	\$170.98 per hour	\$170.98 per hour	\$170.98 per hour	Rate R2 \$170.98 per hour
		6 to 10 lots \$683.94				Rate R3 \$199.27 per hour
		11 - 40 lots \$1196.89				Rate R5 - major \$252.58 per hour
		Over 40 lots \$1538.86				
		URD including Kiosk/HVC/PT (NEW)				
		\$641.19 per substation				
		Chamber Substation, Multiple Kiosk Installation and Sydney Central Business District Substation (Quoted - hourly rate)				
		\$170.98 per hour				



Clause	Ancillary service	Underground urban residential subdivision (vacant lots)	Rural overhead subdivisions and rural extensions	Underground commercial and industrial or rural subdivisions (vacant lots - no development)	Commercial and industrial developments	Asset relocation or street lighting
B2	Design certification	Underground urban residential subdivision (vacant lots) (per service)	Rural overhead subdivisions and rural extensions (per service)	Underground commercial and industrial or rural subdivisions (vacant lots - no development) (per service)	Commercial and industrial developments (Quoted - hourly rate)	Asset relocation or street lighting (Quoted - hourly rate)
		Up to 5 lots    \$341.97	1 - 5 poles    \$341.97	Up to 10 lots    \$512.95	\$199.27                      per hour	Rate R2    \$170.98    per hour
		6 to 10 lots    \$512.95	6 -10 poles    \$512.95	11 - 40 lots    \$683.94		Rate R3    \$199.27    per hour
		11 - 40 lots    \$854.92	11 or more poles    \$854.92	Over 40 lots    \$1,025.91		
		Over 40 lots    \$1,025.91				
		Kiosk Substation , High Voltage Connection and Pole Transformer				
		\$1,025.91    plus charge per lot				
		Chamber Substation , Multiple Kiosk Installation and Sydney Central Business District Substation (Quoted - hourly rate)				
		\$170.98    per hour				
B3	Design rechecking	Underground urban residential subdivision (vacant lots) (Quoted - hourly rate)	Rural overhead subdivisions and rural extensions (Quoted - hourly rate)	Underground commercial and industrial or rural subdivisions (vacant lots - no development) (Quoted - hourly rate)	Commercial and industrial developments (Quoted - hourly rate)	Asset relocation or street lighting (Quoted - hourly rate)
		\$170.98    per hour	\$170.98    per hour	\$170.98    per hour	normal    \$199.27    per hour major connection    \$252.58    per hour	normal    \$199.27    per hour major connection    \$252.58    per hour

Clause	Ancillary service	Underground urban residential subdivision (vacant lots)	Rural overhead subdivisions and rural extensions	Underground commercial and industrial or rural subdivisions (vacant lots - no development)	Commercial and industrial developments	Asset relocation or street lighting
B4	Inspection of service work (by Level 1 ASP)	Underground urban residential subdivision (vacant lots)	Rural overhead subdivisions and rural extension	Underground commercial and industrial or rural subdivisions (vacant lots - no development)	Commercial and industrial developments (Quoted - hourly rate)	Asset relocation or street lighting (Quoted - hourly rate)
		Grade: A per lot, B per lot, C per lot	Grade: A per pole, B per pole, C per pole	Grade: A per lot, B per lot, C per lot	Rate R2 \$170.98 p/hr, Rate R3 \$199.27 p/hr, Rate R5 major \$252.58 p/hr	Rate R2 \$170.98 p/hr, Rate R3 \$199.27 p/hr, Rate R5 major \$252.58 p/hr
		First 10 lots: \$85.50, \$205.18, \$427.47	1 - 5 poles: \$102.60, \$205.18, \$376.16	First 10 lots: \$85.50, \$205.18, \$427.47		
		Next 40 lots: \$51.29, \$119.69, \$256.48	6 - 10 poles: \$85.50, \$170.98, \$341.97	Next 40 lots: \$85.50, \$205.18, \$427.47	plus \$85.50	plus \$85.50
		Remainder: \$17.10, \$68.39, \$119.69	11+ poles: \$68.39, \$119.69, \$256.48	Remainder: \$85.50, \$205.18, \$427.47	flat fee (travel time) per service	flat fee (travel time) per service
		plus \$85.50 flat fee (travel time) per service	plus \$85.50 flat fee (travel time) per service	plus \$85.50 flat fee (travel time) per service		
	High voltage or low voltage underground joint, Air Break Switch, Enclosed Switch, Overhead Underground Connection. \$512.95 plus charge per lot	Decommission a substation. \$1,367.88 plus charge per lot	Substation Inspection (kiosk or pole transformer) or High Voltage Switchgear cubicle. \$1,196.89 plus charge per lot			
B5	Access permit	Underground urban residential subdivision (vacant lots)	Rural overhead subdivisions and rural extensions.	Underground commercial and industrial or rural subdivisions (vacant lots - no development)	Commercial & industrial developments	Asset relocation or street lighting
		\$2,179.62 per service	\$2,179.62 per service	\$2,179.62 per service	\$2,179.62 per service	\$2,179.62 per service
	Complex and Chamber substations (Quoted - hourly rate)	\$170.98 per hour				

Clause	Ancillary service	Underground urban residential subdivision (vacant lots)	Rural overhead subdivisions and rural extensions	Underground commercial and industrial or rural subdivisions (vacant lots - no development)	Commercial and industrial developments	Asset relocation or street lighting		
B6	Contestable Substation Commissioning	Underground urban residential subdivision (vacant lots)	Rural overhead subdivisions and rural extensions.	Underground commercial and industrial or rural subdivisions (vacant lots - no development)	Commercial & industrial developments (Quoted - hourly rate)	Asset relocation or street lighting (Quoted - hourly rate)		
		\$2,154.22 per service	\$1,269.91 per service	\$2,864.77 per service	\$170.98 per hour	\$170.98 per hour		
		Complex and Chamber substations (Quoted - hourly rate) \$170.98 per hour						
B7	Administration Services	Underground urban residential subdivision (vacant lots)	Rural overhead subdivisions and rural extensions.	Underground commercial and industrial or rural subdivisions (vacant lots - no development) (Quoted - hourly rate)	Commercial and industrial developments (Quoted - hourly rate)	Asset relocation or street lighting (Quoted - hourly rate)		
		Up to 5 lots	\$426.52 per service	Up to 5 poles	\$426.52 per service	\$106.63 per hour (max 6 hours)	\$106.63 per hour	
		6 - 10 lots	\$533.15 per service	6-10 poles	\$533.15 per service			
		11 - 40 lots	\$746.41 per service	11 or more poles	\$959.67 per service			
		Over 40 lots	\$853.04 per service					
		Subdivisions involving substations \$127.95 per service						
		Additional services required by ASP/Applicant e.g. Guarantee of revenue, clarification meetings, variations to contract, reinspections etc. (Quoted - hourly rate)						
		\$106.63 per hour						
B8	Notice of arrangement	\$556.04 per notice						
B9	Access (Standby person)	Quoted - hourly rate \$158.52 per hour						
B10	Inspection of service work (by Level 2 ASP)	All Service connections	A Grade \$35.21 per service	B Grade \$60.86 per service	C Grade \$197.65 per service			

Clause	Ancillary service	Underground urban residential subdivision (vacant lots)	Rural overhead subdivisions and rural extensions	Underground commercial and industrial or rural subdivisions (vacant lots - no development)	Commercial and industrial developments	Asset relocation or street lighting
B11	Re-inspection of Level 1 and Level 2 ASP	(NOSW = Notification of Service Work) - (Quoted - per hour)	L1 - network construction \$170.98 per hour	L2 (NOSW) \$199.27 per hour	L1 or L2 major connection	\$252.58 per hour
B12	Clearance To Work	\$1,111.41 per service				
B13	Site Establishment	\$62.74 per service				
B14	Customer Interface Coordination for Contestable Works	Quoted - hourly rate \$239.25 per hour				
B15	Preliminary Enquiry Service	Quoted - hourly rate \$241.92 per hour				
B16	Connection Offer Service	<p><b>Basic Connection Offers</b></p> <p>Basic 100A Connections NOT requiring a load slip \$8.88 per service</p> <p>Over 100A Connection Offer (new or existing site) \$225.93 per service</p> <p>Basic 100A Connections requiring a load slip \$225.93 per service</p> <p>Basic Micro Embedded Generator over 5kW \$225.93 per service</p> <p><b>Standard Connection Offers</b></p> <p>Standard Off Site or On Site Augmentation Work \$225.93 per service</p> <p>Standard Offer ASP1 Connections \$288.94 per service</p> <p>Standard Embedded Generation &gt;5MVA capacity (Quoted - hourly rate) \$252.58 per hour</p>				

Clause	Ancillary service	Underground urban residential subdivision (vacant lots)	Rural overhead subdivisions and rural extensions	Underground commercial and industrial or rural subdivisions (vacant lots - no development)	Commercial and industrial developments	Asset relocation or street lighting
B17	Connection / Relocation Process Facilitation	Quoted - hourly rate	\$241.92 per hour			
B18	Planning Studies and analysis.	Related to distribution (including sub-transmission and dual-function assets) connection applications (Quoted - hourly rate)	\$252.58	per hour		
B19	Deeds of Agreement Service	Services involved in obtaining deeds of agreement in relation to property rights associated with contestable connection works (Quoted - hourly rate)	\$252.58	per hour plus legal costs		
B20	Reinspection of installation work in relation to customer assets	Installation (Certificate of Completion of Electrical Works) (Quoted - hourly rate)	\$170.98	per hour		

**Notes:**

**Lots**

Where an ancillary service relates to a service connection required for multiple dwelling subdivisions, the per lot fee in Table 2 will be applied per service connection

**Overtime**

If an ancillary service is provided outside the hours of 7.30am and 4.00pm on a working day at the request of a customer (other than where Ausgrid requires that the work be performed outside those hours) Ausgrid will charge 175% of the charge for that service carried out in normal working hours shown in Table 3 below.

**Inspection of works**

Level 1 ASP: In the case of 'Commercial and industrial developments' and 'Asset relocation or street lighting', the level of inspection will be determined by Ausgrid, prior to performing the service.

The grade specified (A, B or C) is the grade of the ASP accredited for that grade.

**Substation commissioning**

Other than in the case of 'Underground urban residential subdivision (vacant lots)', the charge specified only applies to a single transformer/RMI unit. In all other cases the service is to be charged at the rate of Table 3 below.

Table 3 below provides details of the hourly labour rates for various classes of labour. Ausgrid will determine whether the service is to be provided by a technician or an engineer at that class, depending on the nature and complexity of the service. Labour rates have been set by the *AER* by reference to five different classes of labour: R1 to R5.

**Table 3: Hourly labour rates (prices include GST)**

Rate	Labour class	Hourly rate	Hourly rate
		Normal Time	Overtime
R1	Admin	\$106.63	\$186.60
R2	Technical	\$170.98	\$299.22
R3	Engineer	\$199.27	\$348.73
R4	Field Worker	\$158.52	\$277.41
R5	Senior engineer	\$252.58	\$442.01

Prices are inclusive of GST

#### **B1 Design Information**

The provision of information by Ausgrid to enable an *ASP* (Level 3) to prepare a design drawing and to submit it for certification.

This may include without limitation:

- deriving the estimated loading on the system, technically known as the After Diversity Maximum Demand (ADMD). This estimate depends on such factors as the number of customers served and specific features of the customer's demand;
- copying drawings that show existing LV and HV mains (geographically and schematically) and adjacent project drawings;
- specifying the preferred sizes for overhead conductors or underground cables;
- specifying switchgear configuration type, number of pillars, streetlights etc.
- determining the special requirements of Ausgrid's planning departments necessary to make electrical supply available to a development and cater for future projects;
- any necessary liaison with designers associated with assistance in sourcing design information and developing designs; or
- nominating network connection points.

#### **B2 Design Certification**

A certification by Ausgrid that a design (if implemented) will not compromise the safety or operation of Ausgrid's distribution system.

This may include, without limitation:

- certifying that the design information / project definition have been incorporated in the design;
- certifying that easement requirements and earthing details are shown;
- considering design issues, including checking for over-design and mechanisms to permit work on HV systems without disruption to supply to customers (adequate LV parallels);
- certifying that funding details for components in the scope of works are correct;
- certifying that there are no obvious errors that depart from Ausgrid's design network standards and specifications;
- certifying that shared assets are not over-utilised to minimise developer's connection costs and that all appropriate assets have been included in the design;
- auditing design calculations such as voltage drop calculations, overhead conductor clearances (stringing) calculations etc.
- certifying that a bill of materials has been submitted; or

- certifying that an environmental assessment has been submitted by the ASP and appropriately checked.

**B3 Design Rechecking**

The rechecking of a design submitted for certification, except where the modifications to a design are of a trivial or minor nature.

**B4 Inspection of Level 1 ASP Work**

Inspection by Ausgrid of work undertaken by a Level 1 ASP, for the purpose of ensuring the quality of assets to be handed over to Ausgrid.

**B5 Access Permits**

The provision of an access permit by Ausgrid to a person authorised (or observed) by Ausgrid to work on or near Ausgrid's distribution system. This service fee includes HV access and may include without limitation:

- Researching and documenting the request for access including a site visit as required;
- Documenting the actual switching process;
- Programming the work;
- Fitting and removing of access permit earths;
- The actual switching of the High Voltage network including travel costs;
- Identification of any customers who will be interrupted for carding by the ASP;
- Low voltage switching and paralleling of substations that permits high voltage work without disrupting supply to other customers;
- Cable ID, stab, cut and phase;
- Reinstate network and testing;

This service excludes provision of temporary generators and Live Line operations to maintain supply. These are services are an additional cost and covered by another quoted service;

**B6 Contestable Substation Commissioning**

The commissioning by Ausgrid of a new substation, [kiosk or chamber] and includes all necessary pre-commissioning checks and tests prior to energising the substation via the high voltage switchgear and closing the low voltage circuit breaker, links or fuses and the setting or resetting of protection equipment and updating of engineering systems.

**B7 Administration Services For ASPs**

Work of an administration nature (not including work of an administrative nature described in service - Notice of Arrangement or Authorisation of ASPs), including the processing of Level 1 and/or Level 3 work where the customer is required to pay for the Level 1 and / or Level 3 work.

This may include without limitation:

- Checking supply availability;
- Processing applications;
- Correspondence from application to completion;
- Record – keeping;
- Requesting and receiving fees (initially, then prior to design and after certification);
- Receiving design drawings (registering and copying);
- Raising order for high voltage (HV) work;
- Calculating HV reimbursements;
- Calculating the cost of a project and warranty / maintenance bond;
- Organising refunds to developers for HV work;
- Liaising with developers via phone and facsimile;
- Updating Geographic Information Systems (GIS) and mapping;
- Supporting the process of design information, design certification and design rechecking.

**B8 Notices of Arrangement**

Work of an administrative nature performed by a Distribution Network Service Provider (DNSP) where a local council requires evidence in writing from a DNSP that all necessary arrangements have been made to supply electricity to a development.

This may include without limitation:

- Receiving and checking linen plans and 88B Instruments;
- Checking and recording easement details;
- Prepare records for conveyance officers;
- Liaise with developers if errors occur or changes are required;
- Check and receive duct declarations and any amended linen plans and 88B instruments approved by a conveyance officer;
- Confirm the works are completed in accordance with Ausgrid's requirements including substations and ducts, service mains to the customer's 'point of supply' and peg all easements and lot frontages and complete the works;
- Prepare notification of arrangement.

Ausgrid however, may issue a NoA prior to completion of the *contestable* works provided:

- the *contestable* design has been certified, and
- an additional bond has been deposited as a Banker's Guarantee, consisting of an amount equal to the value of the *contestable* works remaining to be completed that is returned if all of the above requirements have been satisfied.

#### **B9 Access (Standby Person)**

The provision of access to switch rooms, substations and the like to an *ASP* who is accompanied by a member of staff of Ausgrid, but does not include the circumstance where an *ASP* is provided with keys for the purpose of securing access and is not accompanied by a member of staff of Ausgrid. Preparation of Clearance to Work (CTW) is included and charged in the hourly rate so additional CTW fee not applicable.

#### **B10 Inspection of Service Work (Level 2)**

The inspection by Ausgrid, in accordance with the DTIRIS Accreditation of Service Providers Scheme of work undertaken by a Level 2 *ASP*, for the purpose of ensuring the quality of assets to be handed over to Ausgrid.

The minimum number of inspection required must correspond to the grade of the DNSP as shown:

Grade of ASP	Number of inspections
A	1 Inspection per 20 jobs
B	1 Inspection per 5 jobs
C	Each job to be inspected

#### **B11 Re-Inspection of Level 1 and Level 2 ASP Work**

The re-inspection by Ausgrid of private electrical wiring work undertaken by an electrical contractor, required where the first inspection revealed defective work.

Note: no charge applies where DNSP carries out an initial inspection of private electrical installation work, during normal working hours, which has been notified by a Certificate of Compliance - Electrical Work (CCEW) form.

The service is applied when the inspector identifies a defect within an installation and issues a defect notice. Where more than one dwelling is found to be defective within a multi-unit complex the service should be applied to each of these individual units.

#### **B12 Clearance to Work**

The provision of a clearance to work by Ausgrid to a person authorised to work on or near the system generally at a low voltage.

May include (inter alia):

- Researching and documenting the request for the Clearance to Work
- Operate the Low Voltage network including travel costs
- Identification of all customers who will be interrupted for ASP to notify
- Excludes provision of a temporary generator to maintain supply. These are services in addition and covered by a quoted service
- Reinstate network and testing

#### **B13 Site Establishment**

Site establishment services, including issuing of meters (where applicable) and liaising with Australian Energy Market Operator (AEMO) or market participants for the purpose of establishing National Meter



Identifiers (NMI) in market systems, for new premises or for any existing premises for which AEMO requires a new NMI and for validation of and updating network load data.

Ausgrid may be notified to conduct this service via the use of the 'Allocate NMI' B2B service order.

#### **B14 Customer Interface Coordination**

This service is proposed where customer developments may require a high level of Ausgrid involvement in order to coordinate a range of inputs from Ausgrid to help establish the development. Usually projects with the following characteristics:

- Multiple components. For example, relocation and connection works associated with the one development, or works  $\leq 11$  kV and works at higher voltages.
- Projects with scheduling challenges such as rapid deployment requirements or constrained timeframes for particular tasks.
- Multiple and/or conflicting works to be undertaken in tandem or cooperation with other services or utilities.
- Projects where there are significant inter-relationships between capital and *contestable* works that would benefit from coordination.

The form of this service includes, but is not limited to, attendance at internal and external project meetings in accordance with the needs of particular customers. It requires strong communication skills and technical understanding. The nature of the project would determine the skill level of the assigned officer and the number of hours required.

#### **B15 Preliminary Enquiry Service**

Providing prospective connection applicants with specific information and advice in relation to the connection process and requirements associated with establishing a new or altered connection or a relocation of existing network assets. This service is for initial advice and excludes more detailed investigations/advice that may subsequently be required from Strategic Planning Studies and Analysis and Process Facilitation.

This service includes an initial site inspection and preparation of a written response addressing the issue(s) queried by the applicant. It may also include an initial customer meeting where requested. Enquiries where the enquirer is only seeking information that can be answered by referring to the correct part of the website would not be charged. However more involved responses where the cost to serve is more appropriately born by the applicant would be charged at the relevant fee for this optional service.

#### **B16 Connection Offer Service**

Services provided by Ausgrid in assessing connection applications and making basic or standard connection offers under the NECF framework.

Basic = involves minimal or no augmentation of the network (Basic 100A, Basic over 100A, Basic micro embedded generator (EG))

Standard = model standing offer applies (substation off-site, substation on-site, substation upgrade)

This may include without limitation:

- Assessment of application by Team Leader.
- If the application is deemed to require a basic connection offer service the application is forwarded to Customer Operations who will process the offer.
- If the application is deemed to require a standard connection offer service the application is allocated to Contestability.

Contestability is responsible for deriving the estimated loading on the electrical distribution network, technically known as the ADMD (After Diversity Maximum Demand). This estimate depends on such factors as the number of customers served and specific features of the customer's demand.

Once the ADMD is derived the customer is advised what is required to connect to the electrical distribution network. This could be one of the following methods of supply;

- A direct distributor from an existing substation,
- A direct distributor from a new kiosk substation,
- A direct distributor from a new pole mounted transformer substation,
- A direct distributor from a new chamber substation.

Once the assessment has been completed by Contestability, Administration staff forward the assessment of the standard connection offer to the customer.

### **B17 Connection / Relocation Process Facilitation**

Providing connection applicants with ongoing information and advice in relation to the connection process and requirements associated with establishing a new or altered connection or a relocation of existing network assets. This service is additional to the published instructions available to all applicants and is not a mandatory requirement of the connection process for standard connections to the distribution network ( $\leq 11\text{kV}$ ). It would be recommended for first time *contestable* customers or customers with complex or challenging projects. The intent would be to help minimise project delays caused by customers not taking the required action at the optimum time in the process. This would be achieved by staff taking a proactive approach to communication and engagement with connection applicants. It is an essential requirement for major connection projects (greater than 10MW load or connected at  $>11\text{ kV}$ ) because the process varies to meet particular project requirements (the electrical component potentially being a smaller but often critical part of a much larger project).

The form of this service includes, but is not limited to,

- Project coordination activities;
- One-on-one engagement to review project or process particulars;
- Consultation of connection particulars;
- Facilitation

### **B18 Planning Studies and Analysis Service**

This service undertakes necessary planning studies and associated technical analysis to help determine suitable/feasible connection options for further consideration by proponents. The service applies mainly to large loads and generators where suitable connection options are not necessarily obvious and may result in potentially significant impacts on Ausgrid's existing network development strategies and augmentation requirements.

For some projects a technical assessment of a nominated option may need to be explored to ensure sufficient cost and timing certainty for an applicant and to help underpin subsequent connection offers. A detailed report or reports are provided as agreed and form a basis for the customer's final proposal.

### **B19 Deeds of Agreement Service**

Services related to the acquisition of tenure over and access to Ausgrid assets associated with *contestable* connection works. New assets being connected to the network may be positioned on land not legally accessible to Ausgrid. To ensure Ausgrid has appropriate tenure and access to these new assets into the future, a Deed of Agreement is established in advance of connecting the new assets to facilitate the necessary execution of formal arrangements that create appropriate easement or lease arrangements to be registered on the land title deed.

Services provided in relation to obtaining deeds of agreement for property rights associated with *contestable* connection works, including processes associated with obtaining registered leases and easements for land on which Ausgrid assets are located (i.e. those assets assigned or "gifted" to Ausgrid on electrification). These property rights are necessary in order to ensure that the Ausgrid is able to carry out ongoing maintenance in relation to its assets. As Ausgrid often connects assets before registered leases or easements have been obtained, it is necessary to obtain deeds of agreement from landowners in the interim.

### **B20 Reinspection of installation work in relation to customer assets**

The re-inspection by a DNSP of private electrical wiring work undertaken by an electrical contractor, required where the first inspection revealed defective work.

Note: no charge applies where DNSP carries out an initial inspection of private electrical installation work, during normal working hours, which has been notified by a Certificate of Compliance - Electrical Work (CCEW) form.

The service is applied when the inspector identifies a defect within an installation and issues a defect notice. Where more than one dwelling is found to be defective within a multi-unit complex the service should be applied to each of these individual units.

## Appendix C: Metering Services and Metering related Ancillary Services

### Metering services

#### Metering Connection Charges

From 1 July 2015, the regulation of metering services provided by Ausgrid will change. As a result, a separate charge for the provision of new and upgraded meters will apply.

The charge will be levied when the ASP2 notifies Ausgrid that a meter has been installed or changed. The charge will reflect the type of meter that has been provided by Ausgrid. We consider this charge forms part of the connection charges and therefore forms part of this connection policy. The charge is called a new or upgraded metering charge.

Other charges associated with other meter services such as meter maintenance, meter data services, meter reading and meter replacement are not connection charges as they are part of the ongoing service that Ausgrid provides.

**Table 4: New or upgraded metering charges**

Meter Code	Description	Fee per Meter
B1	Single Phase Single Element Two Wire Direct Connected Accumulation Watt-hour Meter	\$55.28
B3	Three Phase Single Element Four Wire Direct Connected Accumulation Watt-hour Meter	\$143.68
E1	Single Phase Single Element Two Wire Direct Connected Interval Watt-hour Meter	\$134.69
E2	Single Phase Dual Element Two Wire Direct Connected Interval Watt-hour Meter	\$205.62
E3	Three Phase Single Element Four Wire Direct Connected Interval Watt-hour Meter	\$277.99
E4	Three Phase Single Element CT Connected Interval Watt-hour Meter	\$671.31

Prices are inclusive of GST

## Metering related Ancillary services

**Table 5: Metering Ancillary Services required for Connection**

C1	Franchise CT Meter Install	\$0.00 (Under Review)
----	----------------------------	--------------------------

### C1 Franchise CT meter install

Ausgrid is responsible for Type 5 and 6 metering installations connected to Ausgrid's network and must provide and install rule compliant metering for any new current transformer or current and voltage transformer installations.

**Table 6: Metering Ancillary Services after connection**

C2	Special Meter Reading Type 5 and Type 6 Meters	\$11.60
C3	Testing Type 5 and 6 Meters	\$656.48
C4	Not used	Not used
C5	Request for Customer Energy Consumption Data, Tariff or Distribution Information	\$16.56
C6	Emergency maintenance of failed metering equipment not owned by Ausgrid	\$187.71
C7	Controlled Load Conversion	\$237.53
C8	Network Tariff Change Request	\$0.00 (No AER Rate)

Prices are inclusive of GST

### C2 Special Meter Reading

This service has the same meaning as the meaning given to the expression 'special meter reading' in the AEMO Metrology Procedure: Part A National Electricity Market.

Ausgrid may be notified to conduct this service via the use of the 'Special Read' B2B service order. It excludes any special meter reading of metering installation types 1 to 4, which is an unregulated distribution service, but subject to a 'light-handed' form of control under Independent Pricing and Regulatory Tribunal of NSW (IPART) Rule 2004/1 Regulation of Excluded Distribution Services; and applies in each of the following circumstances:

- where a customer or a retail supplier requests Ausgrid to undertake a special meter read, (but does not apply where the special meter read was requested solely to verify the accuracy of a scheduled meter read and the special meter read reveals that the scheduled meter read was inaccurate or in error); or
- where Ausgrid attends at a customer's premises for the sole purpose of discharging Ausgrid's obligation to read the customer's meter within the period specified by law (but not where Ausgrid merely chooses to read the customer's meter without being under a legal obligation to do so) and on attending the customer's premises Ausgrid is unable (through no act or omission of Ausgrid), to gain access to the meter; or
- where Ausgrid and the customer agree on an appointed time at which Ausgrid may attend the customer's premises to enable Ausgrid to discharge Ausgrid's legal obligation referred to in the above paragraph and when Ausgrid attended at the customer's premises at the appointed time Ausgrid (through no act or omission of Ausgrid), was unable to gain access to the customer's meter.

A charge will not be levied for this service ('special meter reading') in either of the following circumstances:

- where the customer is or is about to move premises; or

- where the service reveals that a scheduled meter reading was inaccurate, (as outlined above).

**C3 Testing for type 5 and 6 meter.**

The testing of an Ausgrid meter in accordance with AEMO Metrology Procedure: Part A National Electricity Market. Ausgrid may be notified to conduct this service via the use of the 'Meter Investigation' sub type 'Meter Test' B2B service order. It excludes metering installation types 1 to 4, the testing of which is an unregulated distribution service, but subject to a 'light-handed form of control under IPART Rule 2004/1 Regulation of Excluded Distribution Services.

If the meter test is undertaken on premises serviced by more than one meter associated with the NMI the following applies:

- if the meter test reveals that all of the meters associated with the NMI are operating satisfactorily, Ausgrid will only levy one charge for the provision of the service; and
- if the meter test reveals that one or more of the meters associated with the NMI are not operating satisfactorily, Ausgrid will not levy any charge for the provision of the service.

Test results will be provided to the party requesting the meter tests in a standard Ausgrid format.

**C4 Not used**

**C5 Request for Customer Energy Consumption Data, Tariff or Distribution Information.**

The provision of information of the customer's energy consumption or distributor charges following the request from a Retailer or a Retailer's customer. The energy data will be provided to the Retailer's customer or Retailer in standard market formats.

This fee may only be levied where information is requested more than once in any 12 month period until March 2016 where Rule 86 of the National Electricity Retail Law will require the timing to change to more than four times in any twelve month period.

**C6 Emergency maintenance of failed metering equipment not owned by Ausgrid**

This fee will be levied against the retailer where Ausgrid has been called out by the customer because of a power outage where an external metering providers metering equipment has failed and Ausgrid has had to restore power to the customer's premises. This may result in an unmetered supply arrangement at the site.

The retailer and metering provider will be notified by Ausgrid within 2 business days to arrange a repair by the metering provider.

**C7 Controlled Load Conversion**

The alteration of the off-peak metering equipment at a customer's premises for the purpose of changing the hours of the metering equipment's operation. A charge for this service may be levied for each occasion that the service is provided.

Ausgrid may be notified to conduct this service via the use of the 'Meter reconfiguration' sub type 'Change Controlled Load' B2B service order.

**C8 Network Tariff Change Request**

When a Retailer's customer or Retailer requests an alteration to an existing network tariff (for example, a change from an Inclining Block Tariff or Time of Use tariff to a capacity tariff), Ausgrid conducts tariff and load analysis to determine whether the customer meets the relevant tariff criteria. Ausgrid also processes changes in Ausgrid's IT systems to reflect the tariff change.

This fee will only be levied if after analysis Ausgrid determines that the customer is not eligible for the requested change in network tariff.

Ausgrid is usually notified to conduct this service via the use of the 'Meter Reconfiguration' sub type 'Change Tariff' B2B service order or via the application form in Ausgrid's document ES7 - Application of Network Use of System Charges.

## Appendix D: Miscellaneous Ancillary Services

Table 7: Miscellaneous services

Ref.	Service Name	Service Description	\$	Unit
D1	Authorisation of ASPs	Level 1 ASP	\$647.86	per service
		Level 2 ASP	\$448.60	per service
D2	Conveyancing Information	Supply of Conveyancing information - desk inquiry	\$35.49	per service
		Supply of Conveyancing information – field visit	\$275.77	per service
D3	Disconnection / Reconnection	Disconnection visit (site visit only )	\$50.15	per service
		Disconnection at Meter Box completed (non technical)	\$166.03	per service
		Disconnection at Meter Box Completed ( technical/advanced )	\$279.21	per service
		Disconnection at Pole Top / Pillar Box completed	\$443.52	per service
		Disconnection at Pole Top / Pillar Box (site visit only )	\$370.36	per service
		Disconnection / Reconnection outside normal business hours	\$114.38	per service
D4	Rectification Works	Rectification of illegal connection (fixed fee)	\$897.70	per service
		Provision of Service Crew (per crew , hourly rate)	\$317.03	per hour
		Fitting of Tiger Tails (Job specific , hourly rate)	\$158.52	per hour plus rental of tiger tails
		High Load Escorts (Job Specific, hourly rate)	\$161.63	per hour
D5	Temporary Power	Install and Remove high voltage live line links, Fixed fee	\$6,177.96	per service incl. materials costs
		Break and remake high voltage bonds, Fixed fee	\$3,086.44	per service incl. materials costs
		Break and remake low voltage bonds, Fixed fee	\$2,228.08	per service incl. materials costs
		Connect and Disconnect Motor Generator to overhead mains, Fixed fee	\$3,092.23	per service incl. materials costs
		Connect and Disconnect Motor Generator to low voltage board in a kiosk, Fixed fee	\$2,419.33	per service incl. materials costs

Ref.	Service Name	Service Description	\$	Unit
D6	Investigate, review & implementation of remedial actions associated with ASP's connection works	Hourly rate per investigation	\$252.58	per hour
D7	Debt Recovery	Recovery of dishonoured transactions	\$29.21	per service
D8	Not Used			
D9	Attendance at customers' premises to perform a statutory right where access is prevented	Fee per occurrence	\$90.18	per service
D10	Vacant Property Reconnection or Disconnect. (Includes customer requests for ad-hoc reconnections or disconnections for regular but short periods of time, for example, holiday homes.)	Non-Technical disconnect/reconnect	\$162.90	per service
		Site Visit Only Vacant Property	\$41.58	per service
D11	Move In / Move Out Meter Read	B2B service orders from retailers to obtain a final read for customer move-outs or to obtain a start read where property has been vacant. This includes customer or retailer requests for a final or start read when a customer movement occurs	\$11.04 <sup>2</sup>	per service

Prices are inclusive of GST

#### D1 Authorisation of ASPs

The annual authorisation by Ausgrid of individual employees or sub -contractors of an ASP to carry out work on or near an Ausgrid's distribution and subtransmission system.

This may include without limitation:

- Familiarisation and training in Ausgrid's safety rules;
- Access Permit Recipient training and assessment;
- Induction in the unique aspects of the network;
- Verification that the applicant has undertaken the necessary Regulatory safety training (resuscitation, etc.) within the last 12 months;
- Conducting interviews and examinations and in-field safety audit;
- Issuing authorisation cards;
- Administration support directly related to Authorisation;

#### D2 Supply of Conveyancing Information

##### Desk Inquiry

The provision of information regarding the availability of supply, presence of Ausgrid's equipment, power lines and like information for property conveyancing purposes undertaken without any physical inspection of a site, other than the provision of information or the answering of inquiries relating to any matter under Government Information (Public Access) (GIPA) legislation.

<sup>2</sup> With the AER for review

### **Field Visit**

The provision of information regarding the availability of supply, presence of Ausgrid's equipment, power lines and like information for property conveyancing purposes undertaken solely by a physical inspection of a site, other than the provision of information or the answering of inquiries relating to any matter under GIPA legislation.

## **D3 Disconnection / Reconnection**

### **Disconnection visit (Acceptable Payment Received)**

A site visit to a customer's premises for the purpose of disconnecting the customer's supply at the request of a Retailer based on the customer's breach of a Customer Supply Contract or for breach of Ausgrid's Customer Connection Contract. Disconnection does not occur on that occasion, as customer payment is made or a wasted visit.

Disconnection may not occur because of a number of reasons such as but not limited to the following:

- Customer has paid retail bill;
- Breach of customer connection contract has been rectified;
- Unable to access main switch board or metering;
- Safety of Installation or Ausgrid's employee;
- Late cancellation by Retailer;
- Change of customer or Retailer for the NMI.

Ausgrid is usually notified to conduct this service via the use of the 'De-energisation' B2B service order with sub type 'Remove Fuse (Non Payment)..

### **Disconnection at Meter Box (non technical)**

At the request of the Retailer, a site visit to a customer's premises to disconnect the supply of electricity to a customer for breach by the customer of their customer supply contract or for a breach of Ausgrid's customer connection contract, or where a Retail supplier has requested that the supply to the customer be disconnected.

The disconnection method will be at Ausgrid's discretion and will involve one of the following methods:

- rotate plug in meter; or
- removal of the service fuses; or
- removal of barge board fuses; or
- turn off and sticker covering main switch.

This charge includes the reconnection at the request of the retailer.

If, following a request from a retailer, the reconnection component of this service is provided outside the hours of 7.30am and 4.00pm on a working day, the additional 'Reconnection outside normal business hours' charge, will apply.

Ausgrid is usually notified to conduct this service via the use of the 'De-energisation' B2B service order with sub type 'Remove Fuse (Non Payment).

### **Disconnection at Meter Box (technical/advanced)**

At the request of the Retailer, a site visit to a customer's premises to disconnect the supply of electricity to a customer for breach by the customer of their customer supply contract or for a breach of Ausgrid's customer connection contract, or where a Retail supplier has requested that the supply to the customer be disconnected.

The disconnection method will be at Ausgrid's discretion and will involve a method not identified above (e.g. pull load tail out of meter).

This charge includes the reconnection at the request of the retailer.

If, following a request from a retailer the reconnection component of this service is provided outside the hours of 7.30am and 4.00pm on a working day, the additional 'Reconnection outside normal business hours' charge, will apply.

Ausgrid is usually notified to conduct this service via the use of the 'De-energisation' B2B service order with sub type 'Remove Fuse (Non Payment)', 'Remove Fuse', 'Sticker' or subtype not specified.



### **Disconnection at Pole Top / Pillar Box**

A site visit to a customer's premises to disconnect the supply of electricity to a customer at the pole top or pillar box for breach by the customer of their customer supply contract or for a breach of Ausgrid's customer connection contract, or where a Retailer supplier has requested that the supply to a customer be disconnected, where the customer has denied access to the meter or had prior to the visit, reconnected supply without authorisation by Ausgrid following a previous disconnection.

This charge includes the reconnection at the request of the retailer.

If following a request from a retailer the reconnection component of this service is provided outside the hours of 7.30am and 4.00pm on a working day, the additional 'Reconnection outside normal business hours' charge, will apply.

Ausgrid is may be notified to conduct this service via the use of the 'De-energisation' B2B service order with sub type 'Pillar-Box, Pit or Pole-Top' or 'Pillar-Box, Pit or Pole-Top (Non Payment)'.

### **Disconnection at Pole Top / Pillar Box (Site Visit Only)**

A site visit to a customer's premises to disconnect the supply of electricity to a customer at the pole top or pillar box for breach by the customer of their customer supply contract or for a breach of Ausgrid's customer connection contract, or where a Retailer supplier has requested that the supply to a customer be disconnected, where the customer has denied access to the meter or had prior to the visit, reconnected supply without authorisation by Ausgrid following a previous disconnection. Disconnection does not occur on that occasion, as customer payment is made or a wasted visit.

Disconnection may not occur because of a number of reasons such as but not limited to the following:

- Customer has paid retail bill;
- Breach of customer connection contract has been rectified;
- Safety of Installation or Ausgrid's employee;
- Late cancellation by Retailer;
- Change of customer or Retailer for the NMI.

Ausgrid is may be notified to conduct this service via the use of the 'De-energisation' B2B service order with sub type 'Pillar-Box, Pit or Pole-Top' or 'Pillar-Box, Pit or Pole-Top (Non Payment)'.

### **Disconnections or Reconnections Out of Hours**

At the request of the Retailer:

1. The provision of the re-connection component of either a 'De-energisation' sub type 'Remove Fuse (Non-Payment) or Pillar-Box Pit or Pole-Top (Non-Payment)' B2B service order', carried out, outside the hours of 7.30am and 4.00pm on a working day, or

2. the connection of electricity to a new customer outside the hours of 7:30am and 4:00pm on a working day.

Ausgrid may be notified to conduct this service via the use of the 'Re-energisation' B2B service order.

## **D4 Rectification Works**

### **Rectification of Illegal Connection**

Work undertaken by Ausgrid to its property or the property of another person in order to:

- rectify damage; or
- prevent injury to persons or property,

resulting from conduct that constitutes an offence under Part 6, Division 1 of the Electricity Supply Act 1995 (NSW). For example, to rectify an unauthorised connection to Ausgrid's distribution system.

Note: the supply would be left disconnected until the customer employed their own electrical contractor/ASP to rectify any faulty wiring or equipment that had been interfered with e.g. full replacement of consumer's mains.

### **Additional crew:**

Provision of additional work crew as a customer's request.

### **Fitting of tiger tail:**

Installation of temporary covering (known as 'torapoli pipes' or 'tiger tails') on overhead mains and service lines. Note: Price will also include a rental charge for the use of equipment temporarily installed. NB This does not include the installation of temporary covers by certain ASPs in association with their *contestable* work, in accordance with their Service Provider Authorisation, which is *contestable* work.

**High load escorts:**

Temporary relocation of Ausgrid overhead mains for high vehicle loads and high load escorts.

**D5 Temporary Power**

The provision of temporary supply using an MG (Motor Generator) connected to the network or a direct distributor and/or use of HV Live Line Techniques when required to maintain a continued but temporary supply to otherwise impacted customers during *contestable* connection works. Service is in conjunction with but in addition to access permits and clearance to work.

Cost of MG hire not included as these are commercially available. Note also no allowance for Ausgrid to supply an MG standby technician if required.

**D6 Investigate and Review ASP Connection Works**

The investigation, review and implementation of remedial actions associated with *contestable* connection works, leading to corrective and disciplinary action against an ASP because of unsafe practices, substandard workmanship or other serious circumstances.

**D7 Debt Recovery**

Ausgrid currently incurs costs, including bank fees when a network customer's or ASP's cheque for the payment of network-related services is dishonoured.

**D8 Not Used.**

**D9 Attendance at Customers Premises – Access Prevented**

A follow up attendance at customers' premises to perform a statutory right where access was prevented or declined by the customer on the initial visit.

This task normally involves a meter technician returning to a customer's premises to undertake a service for a second time because of customer dissent during previous visits.

**D10 Vacant Property Disconnection and Reconnection**

**Non Technical**

At the request of the Retailer, a site visit to a customer's premises to disconnect or reconnect the supply of electricity because of:

- a vacant premises; or
- a site where the power is on.

At the request of the customer a site visit to the customer's premises to disconnect or reconnect the supply of electricity.

This charge includes the reconnection at the request of the retailer.

If, following a request from a retailer, the reconnection component of this service is provided outside the hours of 7.30am and 4.00pm on a working day, the additional 'Reconnection outside normal business hours' charge, will apply.

The disconnection/reconnection method will be at Ausgrid's discretion and will involve one of the following methods:

- rotate plug in meter; or
- removal of the service fuses; or
- removal of barge board fuses; or
- turn off and sticker covering main switch.

Ausgrid may be notified to conduct this service from the retailer via the use of the 'De-energisation' B2B service order with sub type 'Sticker', 'Remove fuse' or subtype not specified.

**Site Visit Only**

At the request of the Retailer, a site visit to a customer's premises to disconnect or reconnect the supply of electricity because of:

- a vacant premises; or
- a site where the power is on.

At the request of the customer, a site visit to the customer's premises to disconnect or reconnect the supply of electricity.

Disconnection does not occur on that occasion, as customer payment is made or a wasted visit.

Disconnection may not occur because of a number of reasons such as but not limited to the following:

- Unable to access main switch board or metering;
- Safety of Installation or Ausgrid's employee;
- Late cancellation by Retailer;
- Change of customer or Retailer for the NMI.

Ausgrid may be notified to conduct this service from the retailer via the use of the 'De-energisation' B2B service order with sub type 'Sticker', 'Remove fuse' or subtype not specified.

**D11 Move in move out meter reads**

B2B service orders from retailers to obtain a final read for customer move-outs or to obtain a start read where a customer is moving in to a site that has been vacant.

These services are additional to the special meter reading, disconnection/reconnection and testing services currently included as miscellaneous services.

For move in's, Ausgrid may be notified to conduct this service via the use of the 'Re-energisation' sub type 'New Reading Required, or Retrospective Move -in, or Subtype not specified' B2B service order.

For move out's, Ausgrid may be notified to conduct this service via the use of the 'Special Read' sub type 'Final Read' B2B service order or a 'De-energisation' sub type 'not specified' or 'sticker' or 'remove fuse' B2B service order.

## Appendix E: Pioneer Schemes

In accordance with the *AER Connection Charge Guidelines* connection applicants may be required to make a contribution towards *connection works* that provide a connection to their premises and which were previously funded by another customer (within a 7 year period).

The contribution by a subsequent customer to works previously funded by the original customer will be based on the physical attribute of the asset or the demand of a subsequent customer as applicable.

For new connections less than 50kVA then a pre calculated refund will be used and this is based on length of distribution lines as well as a pre calculated share of any distribution substation.

For new connections over 50kVA then the refund will be based on the demand of the new customer.

Depreciation calculated in accordance with clause E5 will also be taken into account in determining the contribution payable.

### Establishment and Administration of Schemes

A pioneer scheme will be established and administered in accordance with this Appendix in relation to each original customer's connection works (as defined in clause E1.1) of the same category. (For example, if the original customer's works included a distribution line and a substation, then one pioneer scheme will be established for the distribution line and a separate pioneer scheme will be established for the substation).

Ausgrid will bear the cost of establishing and administering the pioneer schemes.

### E1 Contributions by Subsequent New Customers towards Connection Works

#### E1.1 General

Where:

- (a) a customer (the **original customer**) procures and funds, or becomes liable to procure and fund *connection works* (**original customer's works**); and
- (b) within 7 years of the date of the original customer's application for customer connection services with respect to the original customer's works (**refund period**), a new customer then requests customer connection services from Ausgrid; and
- (c) in order to provide those customer connection services to the new customer, Ausgrid will use all or any part of the original customer's works, then the new customer is liable, in addition to paying for any *connection works* for which that customer is liable, to pay Ausgrid a proportion of the costs of the original customer's works, calculated in accordance with clause E1.2 (**cost share refund**).

#### E1.2 Calculation of Cost Share Refund

- (a) Where the new customer's load (as specified in its application for customer connection services) is equal to or less than 50 kVA, the cost share refund will be the lesser of:
  - (i) the **pre-calculated refund** (see clause E1.3); and
  - (ii) the **original customer's outstanding amount** (see clause E1.5).
- (b) Where the new customer's load (as specified in its application for customer connection services) is greater than 50 kVA, the cost share refund will be the lesser of:
  - (i) the **pro-rata refund** (see clause E1.4); and
  - (ii) the **original customer's outstanding amount** (see clause E1.5).

#### E1.3 Pre-calculated Refund

The **pre-calculated refund** (for the purposes of E1.2(a)(i) above) is:

- (a) where the original customer's works are a distribution line, an amount calculated in accordance with the following formula:

$\frac{\text{Cost of original customer's works} \times \text{Depreciation Factor}}{\text{Number of prospective new customers}}$
x
$\frac{\text{Length of original customer's works used by the new customer (km)}}{\text{Total length of original customer's works (km)}}$
x
$\frac{\text{CPI(2)}}{\text{CPI(1)}}$

- (b) where the original customer's works are works other than a distribution line, an amount calculated in accordance with the following formula:

$$\frac{\text{Cost of original customer's works x Depreciation Factor}}{\text{Number of prospective new customers}} \times \frac{\text{CPI(2)}}{\text{CPI(1)}}$$

#### E1.4 Pro-rata Refund

The **pro-rata refund** (for the purposes of E1.2(b)(i) above) is an amount calculated in accordance with the following formula:

$$\frac{\text{Cost of original customer's works x Depreciation Factor}}{\text{New utilisation of original customer's works}} \times \frac{\text{Total utilisation of original customer's works}}{\text{CPI(2)}} \times \frac{\text{CPI(1)}}{\text{CPI(1)}}$$

#### E1.5 Original Customer's Outstanding Amount

The **original customer's outstanding amount** (for the purposes of E1.2(a)(ii) and E1.2(b)(ii) above) is calculated as follows:

$$\frac{\text{Cost of original customer's works x Depreciation Factor}}{\text{Number of prospective new customers less original customer}} \times \frac{\text{Number of prospective new customers}}{\text{CPI(2)}} \times \frac{\text{CPI(1)}}{\text{CPI(1)}} \text{ less total cost share refunds paid by new customers to Ausgrid in respect of those works as at date of new customer's application for customer connection services.}$$

#### E1.6 Minimum Refund

Despite any other provision in this Appendix, a new customer is not liable to pay any cost share refund if the total amount payable to all customers already connected is less than \$1,000 plus CPI.

$$\$1000 + \text{CPI where } \text{CPI} = \text{CPI(2)} / \text{CPI(3)} \text{ ( see Section E1.7 )}$$

#### E1.7 CPI Adjustments

Despite any other provision in E1 of this appendix:

- (i) the formulas in E1.3, E1.4 and E1.5 are deemed not to include any references to CPI in the case where the beginning of the relevant period for the calculation of CPI(2) is less than 12 months after the end of the relevant period for the calculation of CPI(1); and
- (ii) the formula in E1.6 is deemed not to include any references to CPI in the case where the beginning of the relevant period for the calculation of CPI(2) is less than 12 months after the end of the relevant period for the calculation of CPI(3).

#### E1.8 Explanation of Terms in this Appendix

**Cost of original customer's works** means:

- (a) where Ausgrid carried out the original customer's works as an ASP, the actual cost of those works; and
- (b) where an *ASP* carried out the original customer's works, the estimated amount that Ausgrid would have charged to carry out those works.

**CPI(1)** means the average of the consumer price indices (All Groups, All Capital Cities), published by the Australian Bureau of Statistics, for the previous 4 quarters immediately prior to the date that the original customer's works are completed.

**CPI(2)** means the average of the consumer price indices (All Groups, All Capital Cities), published by the Australian Bureau of Statistics, for the previous 4 quarters immediately prior to date of the new customer's application for customer connection services.

**CPI(3)** means the average of the consumer price indices (All Groups, All Capital Cities), published by the Australian Bureau of Statistics, for the previous 4 quarters in the 2013/2014 financial year.

**New utilisation of original customer's works** means:

- (a) where the original customer's works are a distribution line, a figure in kVA.km, representing the new customer's expected load, in kVA (as specified in its application for customer connection services), multiplied by the length of original customer's works used by the new customer, in km; and
- (b) where the original customer's works are works other than a distribution line, a figure in kVA, representing the new customer's expected load (as specified in its application for customer connection services).

**Number of prospective new customers** means the number of new customers (including the original customer) that Ausgrid expects, prior to construction of the original customer's works, will use those works or any part of them during the refund period, determined in consultation with the original customer, and taking into account all relevant factors including (but not limited to):

- the capability of the proposed works,
- the current number of properties that could potentially utilise those works,
- the current zoning of the area and any rezoning proposals,
- any proposed subdivisions or development applications, and
- historical patterns of customer connection in similar areas.

**Total utilisation of original customer's works** means:

- (a) where the original customer's works are a distribution line, a figure in kVA.km, representing the total of the loads of each customer (including the original customer and the new customer) who use or will use the original customer's works, in kVA (as specified in their respective applications for customer connection services), multiplied by the length of distribution line constituting the original customer's works, in km; and
- (b) where the original customer's works are works other than a distribution line, a figure in kVA, representing the total of the loads of each customer (including the original customer and the new customer) who use or will use the original customer's works (as specified in their respective applications for customer connection services).

## **E2 Refunds**

- (1) Where a new customer pays to Ausgrid an amount under E1 of this appendix, Ausgrid will, as soon as practicable after receiving that amount, repay that amount to the then **current owner** of the premises to which the original customer's works were connected.
- (2) Where there are two or more customers constituting the original customer, as a result of Ausgrid requiring those customers to procure and fund their common works together, the repayment by Ausgrid referred to in E1 above must be divided between those customers in accordance with the proportions in which they funded the works.

## **E3 Obligation to Notify**

- (1) Ausgrid will notify all new customers who apply to Ausgrid for customer connection services and who may be obliged to make refunds under an existing refund scheme, and all *ASPs* known to Ausgrid who are likely to have customers who will so apply, of the existence of the refund scheme and that connecting customers may be obliged to contribute towards refund.
- (2) Ausgrid will also notify original customers, to which a refund scheme applies, of the existence of the refund scheme and that they may be entitled to receive a refund.

## **E4 Depreciation Factor**

A straight line depreciation, over a twenty year asset life, is to be applied to unadjusted values to determine the current day depreciated value of the asset.

The depreciation factor is determined as follows:

Deemed asset life (20 years – asset age) / (Deemed life (20 Years))

For example: Cost of line is \$12,000 and actual asset age is 2 years

Depreciation factor is  $(20 - 2) / (20) = 0.9$

Depreciated asset value is  $\$12,000 \times 0.9 = \$10,800$

## Appendix F: Negotiated Connection Offer Hourly Rates

Table 8: Hourly rates for negotiation of a connection offer (prices include GST)

Labour class	Normal time Hourly rate
Engineering Officer	\$241
Engineer	\$253
Senior Engineer	\$315